| BG622 | | | |
|-------|--------------------------|--|--|
| | Pr | oduct Image | Product features |
| | | | ★ Stable 4G connection |
| | | 1 | ★Support AOV working mode |
| | | | ★ Remote active wake-up, two-way voice intercom |
| | | | ★ Quick start, start recording within 400ms |
| | | | |
| | l l | T. | ★ Intelligent detection of human movement, intelligent alarm push |
| | | | ★ 6000mAh battery, low battery warning |
| | | 0 | ★ Low power system optimization |
| | | | ★ Free cloud storage |
| | | | ★ Dual light source, full color day and night |
| | | | ★ Low power and corded power compatible design |
| No. | Sorts | Туре | Parameters |
| | System | Operating system | Linux |
| 1 | | Online visitor | Supports 4 visitors at the same time |
| | | APP | O-KAM Pro |
| | Collection | CPU | T23ZN |
| | | Memory | 512MB |
| | | Image sensor | GC2083 |
| _ | | Min. Illumination | 0.8Lux/F1.4(color mode),0.3Lux/F1.4(B&W mode) |
| 2 | | Lens | Focal length 4mm, 1G3P |
| | | Sensor performance | Support automatic white balance, automatic gain control and automatic backlight compensation |
| | | Pan&tilt | Horizontal 270°, vertical 90° |
| | | Viewing angle | D100° |
| | Video | Night vision | Color night vision, dual light sources, 3pcs dual-color dual light source lights |
| | | Compression standard | MJPEF/JPEG |
| | | Multi stream | Mainstream:1080P/15fps, sub stream:360P/15fps |
| 3 | | IR control | When the IR night vision function is enabled, IR and ICR are automatically detected; when the IR |
| | | | night vision function is disabled, IR is off and ICR is fixed in the day vision mode. |
| | | Bit rate | CBR/VBR two rate control modes, and the output rate range is 128~4096kbps |
| | | Image adjustment | Vertical, horizontal adjustable, OSD display |
| | Audio | Input | Built-in-38dB microphone |
| 4 | | Output | Built-in 8Ω1W speaker |
| 7 | | Sampling frequency/bit width | 8KHz/16bit |
| | | Compression standard/Bit Rate | G711A |
| | Al | Human detection | Human detection, filtering invalid video contents |
| 5 | | Area detection | Free daub, only monitoring the areas concerned by users |
| | | Smart notification sound | Different devices push different sounds, so that you can know exactly which device is triggered |
| | | Intelligent alarm sound | Set different equipment alarm sounds according to different scenarios |
| | | More Al functions (testing) Networking | Pets, vehicles, parcels, etc Use APP to scan the QR code on device to add; Use the device to scan QR code on APP to add |
| | Network Key/interface | Networking | FDD:B1/B3/B5/B8 |
| 6 | | Cat1 China | |
| | | Cat4 Overseas | TDD:B34/B38/B39/B40/B41 European/Japanese/American versions |
| | | Key 1 | On/Off key |
| 7 | | Reset key | long press to restore factory settings |
| 8 | Storage Alarm | External TF card | Support TF card (up to 256GB) |
| | | Cloud storage | Free loop cloud storage |
| | | Sound light alarm | Sound and light alarm |
| | | Alarm detection | Support human detection, PIR detection range: 10 meters |
| 10 | Physical Indicators | Rated voltage | DC5V±5% |
| | | Power supply | Built in 6000mAh battery |
| | | Consumption | Sleep standby 300uA, working: 400MA-1.5A max |
| | | Operating condition | Working temperature: -10 ~ 55°C, working humidity <90% |
| | | Weight | Net weight: 560g; Gross weight: about 1.13KG |
| | | Product size | 115*162*167mm |
| | | Packing list | Camera*1, manual*1, solar panel*1, solar panel bracket*1 |
| | | | |