			4G Doorbell Camera-GD1
Product image			Features
			★4G connection
			\bigstar Microampere Level Low Power Consumption, the standby time can reach more than 3 years with 3 dry cells
			★ Dedicated 4G data card with extremely low charges
			★Support audio calling and snapshot, pictures will be saved in the cloud
			★Support linking with doorbell chimes
			★Low battery warning, App push alerts
No.	Sorts	Туре	Parameters
1	System	Operating system	Open CPU
		APP	Xiaoying ding dong
2	Collection	CPU	Open CPU
		Resolution	640x480
		Lens	D100° wide angle
3	Audio	Input	Built-in -38dB microphone
		Output	Built-in 8Ω1W speaker
		Sampling frequency/bit width	8KHz/16bit
		Compression standard/Bit Rate	G711A
4	Network	Connection	Scan the QR code to add device
		Cat1 China	FDD:B1/B3/B5/B8; TDD:B34/B38/B39/B40/B41
		433 ding dong doorbell chime	1527 million level coding library; One doorbell can be paired with multiple doorbell chimes.
5	Кеу	Ring button	Short press to wake up the doorbell; Long press to restore factory settings
		Restart button	Short press to restart the device
6	LED status	Solid blue	Network connection succeed
		Blinking blue slowly	Network abnormality or not connected to the network
		Blue light off	In sleep mode
7	Physical Indicators	Power supply	3 AA batteries
		Consumption	Sleep current 10uA, working current: 70mA
		Operating condition	Working temperature: -10~55 $^{\circ}$ C, working humidity<90%
		Weight	(Note: in kind prevail)
		Size	Doorbell: 105*48*21mm
		Packing list	Doorbell*1, bracket with double-sided adhesive *1, manual*1, screws*1, doorbell chime*1